

PROIZVOD

FIKSNI BARCODE (QR) SKENER I INTEGRISAN RFID (MIFARE) ČITAČ KARTICA
PART NO: ACAM-Q88

IDEALAN

Za kompleksne sisteme evidencije i kontrole pristupa, proširanja postojećih sistema, dogradnju postojećih sistema i "prolazi" RFID (mifare 13.56MHz) Kartica, barcode papirna karta (1D, 2D) i QR sa mobilnog telefona. Konekcija, po izboru: **wiegand, TTL, RS232 i RS485**

NIŽE U ORIGINALU

QR Code Access Card Reader is our new intelligent Access Card Reader, Fast reading speed, High recognition rate, Strong compatibility, can connect to any **WIEGAND** input controller, widely used at Office access management, Tourism management, Community visitor access management, Administration Service Hall management, Gates access control, Visitors intelligent machines, Smart home; Upgrade old access control systems etc.



Features:

1. DC 12V ~ 1000MA
2. MF Card for choose
3. Identify paper or screen QR Code
4. Support 26/34 weigand output to third party Access Control system
5. RS232, RS485,USB virtual keyboard, USB virtual Serial port, HTTP output, MQTT output optional.

Technical Parameter

Size(L*W*H)	86*86*42mm
Material	Case: PC Identify panel: tempered glass
Interface	Wiegand26,34 ,RS485,RS232,USB,TCP/IP optional
Decoding support	QR code, one dimensional code
Voltage	Support 4-15V Wide voltage input
Current	800mA
Reading directions	Camera centric slant 45°
Reading speed	<200ms
Reading range	0-20CM
Reading feature	auto-induction, beep hint
Light source	With LED light source itself, anti-highlight interference
Decode Mode	Image decoding
Application environment	Temperature:-20~70°C Humidity:10%~90%
Operate system	Windows(XP, 7, 8, 10), Linux
Indicating status light	Red-Work, Green-Feedback, Light Green-Internet
Reading range	3-6CM
Reading card type	MF card



<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="checkbox"/>
485-B	485-A	232-RX	232-TX	WG-D1	WG-D0	TTL-RX	TTL-TX	GND	12V