



FUNKCIONALNOST

- Moderator odabira režim glasanja, na "touch panel", ili Ethernet Komadnoj konzoli
 - Odabira redni broj predloga za koji se glasa, zatim
 - (I) TAJNO glasanje, ili
 - (II) JAVNO glasanje
 - Na svim Glasačkim konzolama u sistemu pali se ZELENA LED indikacija (glasanje u toku)
 - Na svim (LED, ili LCD) displejima pojavi se "treptuće-zeleno" indikacija i tekst "Glasanje u toku"
- Poslanik, kod (A) tipa Glasačke konzole ubaci RFID Karticu
 - Kod tipa (B) Glasačke konzole verifikuje otisak prsta na skeneru
- U oba slučaja automatski se pale LED indikacije na sva tri tastera i isti su aktivni
 - ZELEN - ZA
 - PLAVA - UZDRŽAN
 - CVENA - PROTIV
- Odabura i pritiska željeni taster i automatski se gase sve tri LED indikacije na tasterima
- Tasteri više nisu aktivni, na toj Glasačkoj konzoli
- U bazi se evidentira rekord:
 - | ID BROJ KARTICE MODERATORA | TAJNO | VREME | ODABIR GLASAČA |, ili
 - | ID BROJ KARTICE MODERATORA | JAVNO | VREME | BROJ KONZOLE | ID BROJ KARTICE | ODABIR GLASAČA |
- Za kraj glasanja,
 - Opcija (1) sistem automatski po isteku zadatog vremena za glasane, de-aktivira sve Glasačke konzole i pali LED-CRVENO na istima
 - Opcija (2) moderator pritiska STOP i s izem automatski de-aktivira sve Glasačke konzole i pali LED-CRVENO na istima
- Sve aktivnosti i prate prikazi rezultata glasanja, LED, ili LCD Displejima (Monitorima)





Opcija (A) Glasačka konzola sa RFID čitačem kartica



Opcija (B) Glasačka konzola sa skenerom otiska prsta

